

# Growatt ShineLan-X

- Directe ethernet verbinding
- Plug-en-Play
- Online monitoring
- 1 maand ingebouwde data opslag



P O W E R  
- I N G O  
T O M O -  
R R O W O

**G**ROWATT

[www.ginverter.com](http://www.ginverter.com)

## Hardware parameters

|                   |            |
|-------------------|------------|
| Gegevensinterface | USB        |
| Werkspanning      | 5V(±5%)    |
| Werkstroom        | 400mA      |
| Energieverbruik   | 2W(MAX:3W) |
| Status weergave   | LED        |

## Application parameters

|                             |                          |
|-----------------------------|--------------------------|
| Ondersteunde servers        | ShineServer              |
| Inverter communicatie       | USB(Modbus RTU protocol) |
| Server communicatie         | TCP(Modbus TCP protocol) |
| USB snelheid                | 12M                      |
| Ethernet snelheid           | 10Mbps                   |
| Max. communicatiebereik     | 100m(Direct connection)  |
| Type configureren           | Via APP                  |
| Gegevensoverdrachtsinterval | 5 Minutes                |
| Standaard server-URL        | server.growatt.com       |

## Algemene data

|                        |                |
|------------------------|----------------|
| Afmetingen (B / H / D) | 152/47/28mm    |
| Gewicht                | 84g            |
| Bedrijfstemperatuur    | 30°C ... +60°C |
| Beschermingsgraad      | IP65           |

CE, RoHS